

Tuner Box S

- Micro-sized FM-Tuner
- 99 presets
- Manual or automatic tuning
- Adaptive noise reduction
- High-contrast dot-matrix display
- Display of frequency, preset number, centre of station, Stereo or Mono reception, signal strength, ...
- Trigger switching (on/off)
- Full function IR remote control
- Full metal casework
- faceplate silver or black

FM tuning range	87,5 - 108,5MHz
Number of presets	99
THD	0,05%
Channel separation	30dB
Sensitivity	7dB/µV mono, 17dB/µV stereo
Output	1 pair RCA/Cinch
Antenna input	1 x coax DIN-socket (75 ohms)
Trigger (In & out)	2,5mmm jack plug
Power supply	9V DC / 300mA
Dimension W x H x D	103 x 36 x 103 mm
	103 x 36 x 122 mm (with sockets)
Weight	670g without power supply



Micro-sized FM-Tuner

This small FM-only tuner is full-loaded with high-quality audio and useful features. 99 station presets are more than enough to store your favourite radio stations. **Tuner Box S** can ideally be used in combination with other Box design components. A full functional IR-remote and the high-contrast dot-matrix display make this unit a delight to use!

